SOLID EXIT 2 EMERGENCY EXIT LIGHT Y3171W141





24-230 V centrally supplied emergency exit light with 2-sided pictogram, arrow up, 30 m viewing distance (Invidually packed TWT3171W)

Solid Exit 2 emergency exit light is equipped with a light plate. The luminaire is designed specifically to withstand harsh conditions. It is a 2-sided IP65 enclosure classed luminaire and completely dust and water proof.

Solid Exit 2 is suitable for example for industrial premises and parking halls. Escap and centrally supplied luminaires are also suitable for outdoor use.

Special attention has been paid to the design for easy installation.

We reserve the rights to make modifications without notice. Copyright © 2024 Teknoware. All rights reserved. Date: May 04, 2024 | Source: www.teknoware.com/en/emergency-lighting/solid-exit-2-emergency-exit-light-y3171w141



Teknoware Oy | P.O. Box 19, 15101 Lahti | Ilmarisentie 8, 15200 Lahti Finland Tel +358 3 883 020 | VAT-number FI01494751 | teknoware.com | emexit@teknoware.com

Product Code	Y3171W141
Mounting (standard)	wall, surface
Customs Code	94056080
GTIN Code	6438045022284
ETIM Product Class	EC001957
Length	371 mm
Width	181 mm
Height	232 mm
Weight	1,8 kg
Max Input Power VA	8 VA (24 V), 10,5 VA (230 V)
Max Input Power W	5 W (24 V), 5,5 W (230 V)
Nominal Supply Voltage	24-230 V, 50/60 Hz AC, DC
Protection Class	III(24V),II(230V)
IP Class	IP65
Temperature Range Min - Max	-5+30 °C
Glow Wire Test of Plastic Materials	650 °C
Viewing Distance	30 m
Light Source	LED
Body Material	plastic
Colour	RAL9003
Electrical Installation	2 x 2,5 mm² (24 V), 3 x 2,5 mm² (230 V)

OPTIONAL ACCESSORIES:

OPTIONAL MOUNTING ACCESSORIES FOR EMERGENCY EXIT LIGHTS



Product Code	Product Name	Compatible Product Groups
TWT3006	Solid Suspension Bracket TWT3006	Solid Exit 2 Emergency Exit Lights, Solid: Line Lowbay Emergency Lights, Solid: Line Midbay Emergency Lights, Solid: Zone Lowbay Emergency Llghts, Solid: Zone Midbay Emergency Lights

We reserve the rights to make modifications without notice. Copyright © 2024 Teknoware. All rights reserved. Date: May 04, 2024 | Source: www.teknoware.com/en/emergency-lighting/solid-exit-2-emergency-exit-light-y3171w141



Teknoware Oy | P.O. Box 19, 15101 Lahti | Ilmarisentie 8, 15200 Lahti Finland Tel +358 3 883 020 | VAT-number FI01494751 | teknoware.com | emexit@teknoware.com


Product Code	Product Name	Compatible Product Groups
TWT3001	Solid Recess Mounting Frame TWT3001	Solid Exit Emergency Exit Lights, Solid Exit 2 Emergency Exit Lights, Solid: Line Lowbay Emergency Lights, Solid: Line Midbay Emergency Lights, Solid: Zone Lowbay Emergency LIghts, Solid: Zone Midbay Emergency Lights
TWT3002	Solid Wall bracket TWT3002	Solid Exit Emergency Exit Lights, Solid Exit 2 Emergency Exit Lights, Solid: Line Lowbay Emergency Lights, Solid: Line Midbay Emergency Lights, Solid: Zone Lowbay Emergency LIghts, Solid: Zone Midbay Emergency Lights
TWT3003	Solid Flag bracket TWT3003	Solid Exit Emergency Exit Lights, Solid Exit 2 Emergency Exit Lights, Solid: Line Lowbay Emergency Lights, Solid: Line Midbay Emergency Lights, Solid: Zone Lowbay Emergency Lights, Solid: Zone Midbay Emergency Lights
TWT3004	Solid Ceiling bracket TWT3004	Solid Exit Emergency Exit Lights, Solid Exit 2 Emergency Exit Lights, Solid: Line Lowbay Emergency Lights, Solid: Line Midbay Emergency Lights, Solid: Zone Lowbay Emergency LIghts, Solid: Zone Midbay Emergency Lights


We reserve the rights to make modifications without notice. Copyright © 2024 Teknoware. All rights reserved. Date: May 04, 2024 | Source: www.teknoware.com/en/emergency-lighting/solid-exit-2-emergency-exit-light-y3171w141






10







We reserve the rights to make modifications without notice. Copyright © 2024 Teknoware. All rights reserved. Date: May 04, 2024 | Source: www.teknoware.com/en/emergency-lighting/solid-exit-2-emergency-exit-light-y3171w141



Teknoware Oy | P.O. Box 19, 15101 Lahti | Ilmarisentie 8, 15200 Lahti Finland Tel +358 3 883 020 | VAT-number FI01494751 | teknoware.com | emexit@teknoware.com